



DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

MAX9505

General Description

The MAX9505 filters and amplifies standard-definition video signals. Maxim's DirectDrive™ technology eliminates large output-coupling capacitors and sets the video black level to ground. An internal reconstruction filter smooths the steps and reduces the spikes on the video signal from the video digital-to-analog converter (DAC). The input of the MAX9505 can be directly connected to the output of a DAC. The MAX9505 provides a compact, integrated, and low-power solution.

The reconstruction filter typically has 3dB attenuation at 9MHz and 50dB attenuation at 27MHz, and ± 1 dB pass-band flatness to 5.5MHz.

Maxim's DirectDrive uses an integrated charge pump and a linear regulator to create a negative power supply to drive the sync below ground. The charge pump injects so little noise into the video output that the picture is visibly flawless.

The MAX9505 features an internal 1.7Ω analog switch that interfaces with a 4-pole multimedia jack. This switch allows one of the poles to be set as a video input, a video output, or a microphone input.

The MAX9505 is offered in space-saving 16-pin QSOP and 16-pin TQFN packages and is specified over the -40°C to $+85^\circ\text{C}$ extended temperature range.

Applications

Mobile Phones/Smartphones
Space-Constrained, Low-Power Audio/Video
Portable Devices

Features

- ◆ DC-Coupled Output
- ◆ Direct Connection to Video DAC
- ◆ Video Output Black Level Set to Ground
- ◆ Video Reconstruction Filter with 50dB Attenuation at 27MHz
- ◆ 6dB Gain
- ◆ 1.7Ω R_{ON} Analog Switch
- ◆ 10nA Shutdown Supply Current
- ◆ 2.7V to 3.6V Single-Supply Operation


Ordering Information

PART*	PIN-PACKAGE	PKG CODE	TOP MARK
MAX9505EEE	16 QSOP	E16-4	—
MAX9505ETE	16 TQFN	T1633-4	ACW

*All devices are specified over the -40°C to $+85^\circ\text{C}$ operating temperature range.

Functional Diagram/Typical Operating Circuit and Pin Configurations appear at end of data sheet.

Block Diagram



DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

ABSOLUTE MAXIMUM RATINGS

V_{DD} to SGND -0.3V to +4V
 V_{IDIN} to SGND -0.3V to +4V
 BIAS to SGND -0.3V to ($V_{DD} + 0.3V$)
 $MODE0, MODE1$ to SGND -0.3V to +4V
 $S_{IN}, S_{OUT}, V_{IDOUT}$ to SGND (The greater of V_{SS} and -2V) to ($V_{DD} + 0.3V$)
 CPV_{DD} to CPGND -0.3V to +4V
 $C1P, C1N, CPV_{SS}$ Capacitor Connection Only
 CPGND, SGND, GND -0.1V to +0.1V
 CPV_{SS} to V_{SS} -0.1V to +0.1V

V_{IDOUT} Short Circuit to $V_{DD}, SGND$ and the Greater of (V_{SS} and -2V) Continuous
 Continuous Current
 $V_{IDIN}, BIAS, MODE0, MODE1, S_{IN}, S_{OUT}$ $\pm 20mA$
 Continuous Power Dissipation ($T_A = +70^\circ C$)
 16-Pin QSOP (derate 8.3mW/ $^\circ C$ above $+70^\circ C$) 667mW
 16-Pin TQFN (derate 15.6mW/ $^\circ C$ above $+70^\circ C$) 1349mW
 Operating Temperature Range $-40^\circ C$ to $+85^\circ C$
 Junction Temperature $+150^\circ C$
 Storage Temperature Range $-65^\circ C$ to $+150^\circ C$
 Lead Temperature (soldering, 10s) $+300^\circ C$

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

($V_{DD} = CPV_{DD} = MODE1 = 3.0V$, $MODE0 = SGND = GND = CPGND = 0V$, $C1 = C2 = C3 = C4 = 1\mu F$, $R_{BIAS} = 100k\Omega$, $T_A = T_{MIN}$ to T_{MAX} . $R_L = 150\Omega$ to SGND, unless otherwise noted. $V_{IDIN} = 286mV$, gain = 6dB. Typical values are at $V_{DD} = CPV_{DD} = MODE1 = 3.0V$, $T_A = +25^\circ C$, unless otherwise noted.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
Supply Voltage Range	V_{DD}, CPV_{DD}	Guaranteed by DC voltage gain and quiescent supply current	2.7		3.6	V
Quiescent Supply Current	I_{DD}	$V_{DD} = 3.6V$ ($I_{DD} = I_{VDD} + I_{CPVDD}$, $R_L = \infty$)		12	15	mA
Shutdown Supply Current	I_{SHDN}	$V_{DD} = 3.6V$ ($I_{SHDN} = I_{VDD} + I_{CPVDD}$), $SHDN = SGND$		0.01	1	μA
Bias Voltage	V_{BIAS}			1		V
VIDEO AMPLIFIER						
Input Voltage Range	V_{RANGE}	Guaranteed by DC voltage gain, $V_{DD} = 2.7V$	-0.10		+1.05	V
		Guaranteed by DC voltage gain, $V_{DD} = 3V$	-0.10		+1.28	
Input Current	I_{IN}	$V_{DD} = 2.7V$	-2.5		+2.5	μA
Input Resistance	R_{IN}			1		$M\Omega$
DC Voltage Gain (Note 2)	A_V	$V_{DD} = 2.7V$ to $3.6V$	5.5	6	6.5	dB
Output Black Level (Note 3)		$V_{DD} = 2.7V$	-0.1	0	+0.1	V
Output Voltage Swing		Guaranteed by DC voltage gain, $V_{DD} = 2.7V$	2.162			V_{P-P}
		Guaranteed by DC voltage gain, $V_{DD} = 3V$	2.594			
Output Short-Circuit Current	I_{SC}	Sinking or sourcing		50		mA
Output Resistance	R_{OUT}			0.01		Ω
Shutdown Output Impedance		$MODE1 = MODE0 = SGND$		4		$k\Omega$
V_{IDOUT} Leakage Current		$MODE1 = MODE0 = V_{DD}$		0.01		μA
		$MODE1 = SGND$ and $MODE0 = V_{DD}$		0.01		

DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

ELECTRICAL CHARACTERISTICS (continued)

($V_{DD} = CPV_{DD} = \text{MODE1} = 3.0\text{V}$, $\text{MODE0} = \text{SGND} = \text{GND} = \text{CPGND} = 0\text{V}$, $C1 = C2 = C3 = C4 = 1\mu\text{F}$, $R_{\text{BIAS}} = 100\text{k}\Omega$, $T_A = T_{\text{MIN}}$ to T_{MAX} . $R_L = 150\Omega$ to SGND , unless otherwise noted. $V_{\text{VIDIN}} = 286\text{mV}$, gain = 6dB. Typical values are at $V_{DD} = CPV_{DD} = \text{MODE1} = 3.0\text{V}$, $T_A = +25^\circ\text{C}$, unless otherwise noted.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
ANALOG SWITCH						
On-Resistance	R_{ON}	$\text{MODE0} = V_{DD}$, $I_{\text{SIN}} = 10\text{mA}$	$\text{MODE1} = V_{DD}$	1.7	4.4	Ω
			$\text{MODE1} = \text{SGND}$	1.2	2.5	
On-Resistance Flatness (Note 4)		$\text{MODE0} = V_{DD}$, $I_{\text{SIN}} = 10\text{mA}$, $V_{DD} = 3\text{V}$	$\text{MODE1} = V_{DD}$	0.5	0.9	Ω
			$\text{MODE1} = \text{SGND}$	0.3	0.5	
S_{OUT} Off-Leakage Current (Note 5)		$\text{MODE0} = \text{SGND}$, $V_{DD} = 3.6\text{V}$, $V_{\text{SIN}} = 0.3\text{V}$, 3.3V , $V_{\text{SOUT}} = 3.3\text{V}$, 0.3V	-1		+1	nA
S_{IN} On-Leakage Current (Note 5)		$\text{MODE0} = V_{DD}$, $V_{DD} = 3.6\text{V}$, $V_{\text{SIN}} = 0.3\text{V}$, 3.3V , $V_{\text{SOUT}} = 3.3\text{V}$, 0.3V	-1		+1	nA
Turn-On Time		$V_{\text{SIN}} = 1.5\text{V}$, $R_L = 300\Omega$, $C_L = 35\text{pF}$, Figure 1; $V_{\text{IH}} = 1.5\text{V}$, $V_{\text{IL}} = 0\text{V}$		35	60	ns
Turn-Off Time		$V_{\text{SIN}} = 1.5\text{V}$; $R_L = 300\Omega$, $C_L = 35\text{pF}$, Figure 1; $V_{\text{IH}} = 1.5\text{V}$, $V_{\text{IL}} = 0\text{V}$		50	80	ns
Charge Injection		$V_{\text{GEN}} = 1.5\text{V}$, $R_{\text{GEN}} = 0\Omega$, $C_L = 1\text{nF}$, Figure 2		20		pC
Off-Isolation		$\text{MODE0} = \text{SGND}$, $f = 10\text{MHz}$; $V_{\text{SOUT}} = 1\text{V}_{\text{P-P}}$, $R_L = 50\Omega$, $C_L = 5\text{pF}$		30		dB
		$\text{MODE0} = \text{SGND}$, $f = 1\text{MHz}$; $V_{\text{SOUT}} = 1\text{V}_{\text{P-P}}$, $R_L = 50\Omega$, $C_L = 5\text{pF}$		50		
On-Channel -3dB Bandwidth		$\text{MODE0} = V_{DD}$, signal = 0dBm, $R_L = 50\Omega$, $C_L = 5\text{pF}$		200		MHz
Total Harmonic Distortion		$\text{MODE0} = V_{DD}$, $V_{\text{SIN}} = 2\text{V}_{\text{P-P}}$, $R_L = 600\Omega$		0.025		%
S_{OUT} Off-Capacitance		$\text{MODE0} = \text{SGND}$, $f = 1\text{MHz}$		18		pF
Switch On-Capacitance		$\text{MODE0} = V_{DD}$, $f = 1\text{MHz}$		60		pF
CROSSTALK (VIDEO TO AUDIO)						
VIDIN to S_{IN}		$\text{MODE1} = \text{MODE0} = V_{DD}$, $f = 20\text{kHz}$, $1\text{V}_{\text{P-P}}$ at VIDIN		100		dB
VIDOUT to S_{IN}		$\text{MODE1} = V_{DD}$, $\text{MODE0} = \text{SGND}$, $f = 20\text{kHz}$, $2\text{V}_{\text{P-P}}$ at VIDOUT		85		dB
CHARGE PUMP						
Switching Frequency			150	250	300	kHz
LOGIC SIGNALS (MODE0, MODE1)						
Logic-Low Threshold	V_{IL}	$V_{DD} = 2.7\text{V}$ to 3.6V			0.5	V
Logic-High Threshold	V_{IH}	$V_{DD} = 2.7\text{V}$ to 3.6V	1.5			V
Logic Input Current	I_{IL}				1	μA

DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

AC ELECTRICAL CHARACTERISTICS

($V_{DD} = CPV_{DD} = MODE1 = 3.0V$, $MODE0 = SGND = GND = CPGND = 0V$, $C1 = C2 = C3 = C4 = 1\mu F$, $R_{BIAS} = 100k\Omega$, $T_A = T_{MIN}$ to T_{MAX} . $R_L = 150\Omega$ to $SGND$, unless otherwise noted. $V_{IDIN} = 286mV$, gain = 6dB. Typical values are at $V_{DD} = CPV_{DD} = MODE1 = 3.0V$, $T_A = +25^\circ C$, unless otherwise noted.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
Passband Flatness		$V_{DD} = 2.7V$, $f = 100kHz$ to $5.5MHz$	-1	0	+1	dB
Attenuation		$V_{DD} = 2.7V$, $VIDOUT = 2V_{P-P}$, attenuation is referred to $100kHz$	$f = 9.1MHz$		3	dB
			$f = 27MHz$		35	
Power-Supply Rejection Ratio	PSRR	$f = 100kHz$		62		dB
Output Impedance	Z_{OUT}	$f = 5MHz$		0.5		Ω
Differential Gain Error	DG	NTSC, $VIDOUT = 2V_{P-P}$		0.1		%
Differential Phase Error	DP	NTSC, $VIDOUT = 2V_{P-P}$		0.2		degrees
2T Pulse-to-Bar K Rating		$2T = 250ns$, bar time is $18\mu s$, the beginning 2.5% and the ending 2.5% of the bar time are ignored		-0.3		K%
2T Pulse Response		$2T = 250ns$		0.3		K%
2T Bar Response		$2T = 250ns$, bar time is $18\mu s$, the beginning 2.5% and the ending 2.5% of the bar time are ignored		0.7		K%
Nonlinearity		5-step staircase		0.2		%
Group Delay Distortion	DD_t	$100kHz$ to $5.5MHz$		10		ns
$VIDOUT$ Capacitive-Load Stability	C_L	$V_{OUT} = 2V_{P-P}$, no sustained oscillations		20		pF
Peak Signal-to-RMS Noise	SNR	$100kHz$ to $5.5MHz$		64		dB
Enable Time	t_{ON}	$VIDIN = 0.5V$, $VIDOUT$ settled to within 1% of the final voltage		0.2		ms
Disable Time	t_{OFF}	$VIDIN = 0.5V$, $VIDOUT$ settled to below 1% of the output voltage		0.1		ms

Note 1: All devices are 100% production tested at $T_A = +25^\circ C$. Specifications over temperature are guaranteed by design.

Note 2: Voltage gain (A_V) is a two-point measurement in which the output voltage swing is divided by the input voltage swing.

Note 3: With an output load attached, this offset will directly contribute to quiescent current.

Note 4: Flatness is defined as the difference between the maximum and minimum value of on-resistance as measured over the specified analog signal ranges.

Note 5: Guaranteed by design.

DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

Timing Diagrams




Figure 1. Analog Switch Turn-On/Off Time





Figure 2. Charge Injection

DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

Typical Operating Characteristics







($V_{DD} = CPV_{DD} = MODE1 = 3.0V$, $MODE0 = SGND = GND = CPGND = 0V$, no load, $C1 = C2 = C3 = C4 = 1\mu F$, $R_{BIAS} = 100k\Omega$, $T_A = T_{MIN}$ to T_{MAX} . $R_{IN} = 150\Omega$ to $SGND$, unless otherwise noted. $V_{VIDIN} = 286mV$, gain = 6dB. Typical values are at $T_A = +25^\circ C$, unless otherwise noted.)



DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

Typical Operating Characteristics (continued)







($V_{DD} = CPV_{DD} = MODE1 = 3.0V$, $MODE0 = SGND = GND = CPGND = 0V$, no load, $C1 = C2 = C3 = C4 = 1\mu F$, $R_{BIAS} = 100k\Omega$, $T_A = T_{MIN}$ to T_{MAX} . $R_{IN} = 150\Omega$ to $SGND$, unless otherwise noted. $V_{VIDIN} = 286mV$, gain = 6dB. Typical values are at $T_A = +25^\circ C$, unless otherwise noted.)



DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

Typical Operating Characteristics (continued)

($V_{DD} = CPV_{DD} = MODE1 = 3.0V$, $MODE0 = SGND = GND = CPGND = 0V$, no load, $C1 = C2 = C3 = C4 = 1\mu F$, $R_{BIAS} = 100k\Omega$, $T_A = T_{MIN}$ to T_{MAX} . $R_{IN} = 150\Omega$ to $SGND$, unless otherwise noted. $V_{VIDIN} = 286mV$, gain = 6dB. Typical values are at $T_A = +25^\circ C$, unless otherwise noted.)



DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

Pin Description

PIN		NAME	FUNCTION
QSOP	TQFN		
1	15	VSS	Negative Power Supply. Connect to CPVSS.
2	16	CPVSS	Charge-Pump Negative Power Supply. Bypass with a 1 μ F capacitor to CPGND.
3	1	C1N	Charge-Pump Flying Capacitor Negative Terminal. Connect a 1 μ F capacitor from C1P to C1N.
4	2	CPGND	Charge-Pump Power Ground
5	3	C1P	Charge-Pump Flying Capacitor Positive Terminal. Connect a 1 μ F capacitor from C1P to C1N.
6	4	CPVDD	Charge-Pump Positive Power Supply. Bypass with a 1 μ F capacitor to CPGND.
7	5	BIAS	Common-Mode Voltage. Connect a 100k Ω resistor from BIAS to SGND.
8	6	SGND	Signal Ground. Connect to GND.
9	7	VIDIN	Video Input
10	8	MODE0	Mode Logic Input 0. See Table 1.
11	9	MODE1	Mode Logic Input 1. See Table 1.
12	10	GND	Ground. Connect to SGND.
13	11	VDD	Positive Power Supply. Bypass with a 1 μ F capacitor to SGND.
14	12	SOUT	Analog Switch Output
15	13	VIDOUT	Video Output
16	14	SIN	Analog Switch Input
—	EP	EP	Exposed Paddle. Connect to GND.

Detailed Description

The MAX9505 completely eliminates the need for capacitors in the video output by using Maxim's DirectDrive technology that includes an inverting charge pump and linear regulator. The charge pump and linear regulator create a clean negative supply allowing the amplifier output to swing below ground. The amplifier output can swing both positive and negative so that the video signal black level can be placed at ground. The MAX9505 features a six-pole, Butterworth filter to perform reconstruction filtering on the video input signal from the DAC.

DirectDrive Background

Integrated video filter/amplifier circuits operating from a single, positive supply usually create video output signals that are level-shifted above ground to keep the signal within the linear range of the output amplifier. For applications in which the positive DC level shift of the video signal is not acceptable, a series capacitor can be inserted in the output connection in an attempt to eliminate the positive DC level shift. The series capacitor cannot truly level shift a video signal because the

average level of the video varies with picture content. The series capacitor biases the video output signal around ground, but the actual level of the video signal can vary significantly depending upon the RC time constant and the picture content.

The series capacitor creates a highpass filter. Since the lowest frequency in video is the frame rate, which can be between 24Hz and 30Hz, the pole of the high-pass filter should ideally be an order of magnitude lower in frequency than the frame rate. Therefore, the series capacitor must be very large, typically from 220 μ F to 3000 μ F. For space-constrained equipment, the series capacitor is unacceptable. Changing from a single series capacitor to a SAG network that requires two smaller capacitors can only reduce space and cost slightly.

The series capacitor in the usual output connection also prevents damage to the output amplifier if the connector is shorted to a supply or to ground. While the output connection of the MAX9505 does not have a series capacitor, the MAX9505 will not be damaged if the connector is shorted to a supply or to ground (see the *Short-Circuit Protection* section).

DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch




Figure 3. AC-Coupled Output

Video Amplifier

Typically, the black level of the video signal created by the video DAC is around 300mV. The MAX9505 shifts the black level to ground at the output. Therefore, the active video is above ground, and sync is below ground. The amplifier needs a negative supply for its output stage to remain in its linear region when driving sync below ground.

The MAX9505 has an integrated charge pump and linear regulator to create a low-noise negative supply from the positive supply voltage. The charge pump inverts the positive supply to create a raw negative voltage that is then fed into the linear regulator, which outputs -2V. The linear regulator filters out the charge-pump noise.

Comparison Between DirectDrive Output and AC-Coupled Output

The actual level of the video signal varies less with a DirectDrive output than an AC-coupled output. The video signal average can change greatly depending upon the picture content. With an AC-coupled output, the average will change according to the time constant formed by the series capacitor and series resistance (usually 150Ω). For example, Figure 3 shows an AC-coupled video signal alternating between a completely black screen and a completely white screen. Notice the excursion of the video signal as the screen changes.

With the DirectDrive amplifier, the black level is held at ground. The video signal is constrained between -0.3V to +0.7V. Figure 4 shows the video signal from a DirectDrive amplifier with the same input signal as the AC-coupled system.




Figure 4. DirectDrive Output

Analog Switch

The MAX9505 features an internal 4.4Ω (max) analog normally open switch that interfaces with a 4-pole multimedia jack in which one of the poles can be set to a video input, a video output, or a microphone input. The switch has three modes of operation: open, normal switch, and extended range switch. In normal switch mode, the analog range is from 0V to V_{DD}. In extended-range switch mode, the analog range is from -2V to V_{DD}. Logic inputs MODE1 and MODE0 control the analog switch operating modes (Table 1).

Video Reconstruction Filter

Before the video signal from the DAC can be amplified, it must be lowpass filtered to smooth the steps and to reduce the spikes created whenever the DAC output changes value. In the frequency domain, the steps and spikes cause images of the video signal to appear at multiples of the sampling clock. The MAX9505 contains a six-pole Butterworth lowpass filter. The passband extends to 5.5MHz, and the minimum attenuation is 35dB at 27MHz.

Operating Modes

The MAX9505 uses two logic inputs to set the device into one of the following modes: 1) shutdown mode, 2) extended-range switch mode, 3) video output mode, and 4) normal switch mode.

In video output mode, the video circuitry is on, the charge pump is on, and the analog switch is open. In normal switch mode, the analog switch is closed, and the video circuitry and charge pump are off. In the extended-range switch mode, the charge pump is on and the analog switch is closed. Shutdown mode reduces the supply current to 10nA typically (see Table 1 and *Typical Application Circuits*).

DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

Table 1. Operating Modes

OPERATING MODE	MODE1	MODE0	VIDEO CIRCUIT	CHARGE PUMP	ANALOG SWITCH	COMMENTS
Shutdown Mode	0	0	Off	Off	Open	Video output is 4k Ω and analog switch is open
Extended Range Switch Mode	0	1	Off	On	Closed	Video output is high impedance. Analog switch range is from -2V to V _{DD} .
Video Output Mode	1	0	On	On	Open	Video output is in normal operation. Analog switch is open.
Normal Switch Mode	1	1	Off	Off	Closed	Video output is high impedance. Analog switch range is from SGND to V _{DD} .

Short-Circuit Protection

The MAX9505 typical operating circuit includes a 75 Ω back-termination resistor that limits short-circuit current if an external short is applied to the video output. The MAX9505 features internal output, short-circuit protection to prevent device damage in prototyping and applications where the amplifier output can be directly shorted.

Shutdown

The MAX9505 features a low-power shutdown mode for battery-powered/portable applications. Shutdown reduces the quiescent current to less than 10nA. Setting MODE1 and MODE0 low disables the outputs and places the MAX9505 into a low-power shutdown mode. In shutdown mode the amplifier, charge pump, and linear regulator are turned off and the video output resistance is 4k Ω .

Applications Information


Power-Supply Bypassing and Ground Management

The MAX9505 operates from a 2.7V to 3.6V single supply and requires proper layout and bypassing. For the best performance, place the components as close to the device as possible.


Proper grounding improves performance and prevents any switching noise from coupling into the video signal. Connect GND and SGND together at a single point on the PC board. Route all traces that carry switching transients away from SGND. Return SGND to the lowest impedance ground available. Route CPGND and all traces carrying switching transients away from SGND, GND, and other traces and components in the video signal path. Bypass the analog supply (V_{DD}) with a 1 μ F capacitor to SGND, placed as close to the device as possible. Bypass the charge-pump supply (CPV_{DD}) with a 1 μ F capacitor to CPGND, placed as close to the device as possible. Connect CPV_{SS} to V_{SS} and bypass with a 1 μ F capacitor to CPGND as close to the device as possible.

DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

Pin Configurations



Functional Diagram/Typical Operating Circuits



MAX9505

2.8V FROM LDO

BASEBAND IC

MIC AMP

2k Ω

1 μ F

2k Ω

SOUT

BIAS

100k Ω

V_{DD}

MODE1

MODE0

LOGIC CONTROL

1V

MAXIM

MAX9505

SIN

VIDOUT

75 Ω

1

2

3

4

MIC INPUT

AUDIO OUT LEFT

AUDIO OUT RIGHT

GROUND

4-POLE MULTIMEDIA JACK

SGND

GND

V_{DD}

CPV_{DD}

C4

1 μ F

C3

1 μ F

CPGND

C1P

C1

1 μ F

C1N

CPV_{SS}

V_{SS}


C2

1 μ F

NORMAL SWITCH MODE
POLE 1 USED AS A MICROPHONE INPUT

DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

Functional Diagram/Typical Operating Circuits (continued)



Chip Information


PROCESS: BICMOS

DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

Package Information

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information, go to www.maxim-ic.com/packages.)



MAX9505



DirectDrive Video Amplifier with Reconstruction Filter and Analog Switch

Package Information (continued)

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information, go to www.maxim-ic.com/packages.)



Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

16 **Maxim Integrated Products, 120 San Gabriel Drive, Sunnyvale, CA 94086 408-737-7600**