Analog Multiplexer/ Demultiplexer

TTL Compatible, Single–Pole, 8–Position Plus Common Off

The NLAST4051 is an improved version of the MC14051 and MC74HC4051 fabricated in sub–micron Silicon Gate CMOS technology for lower $R_{DS(on)}$ resistance and improved linearity with low current. This device may be operated either with a single supply or dual supply up to ± 3 V to pass a 6 V_{PP} signal without coupling capacitors.

When operating in single supply mode, it is only necessary to tie V_{EE} , pin 7 to ground. For dual supply operation, V_{EE} is tied to a negative voltage, not to exceed maximum ratings. Translation is provided in the device, the Address and Inhibit are standard TTL level compatible. For CMOS compatibility see NLAS4051. Pin for pin compatible with all industry standard versions of '4051.'

Features

- Improved R_{DS(on)} Specifications
- Pin for Pin Replacement for MAX4051 and MAX4051A - One Half the Resistance Operating at 5.0 V
- Single or Dual Supply Operation
 - Single 3.0 5.0 V Operation, or Dual ± 3 V Operation
 - With V_{CC} of 3.0 to 3.3 V, Device Can Interface with 1.8 V Logic, No Translators Needed
 - Address and Inhibit Logic are Over–Voltage Tolerant and May Be Driven Up +6 V Regardless of V_{CC}
- Address and Inhibit Pins Standard TTL Compatible
 Greatly Improved Noise Margin Over MAX4051 and MAX4051A
 - True TTL Compatibility $V_{IL} = 0.8$ V, $V_{IH} = 2.0$ V
- Improved Linearity Over Standard HC4051 Devices
- Space Saving TSSOP Package
- NLV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC–Q100 Qualified and PPAP Capable
- These Devices are Pb–Free, Halogen Free/BFR Free and are RoHS Compliant





ON Semiconductor®

www.onsemi.com



ORDERING INFORMATION

See detailed ordering and shipping information in the package dimensions section on page 10 of this data sheet.

TRUTH TABLE

Inhibit		Address		ON SWITCHES*					
	С	В	Α						
1	X don't care	X don't care	X don't care	All switches open					
0	0	0	0	COM-NO ₀					
0	0	0	1	COM-NO ₁					
0	0	1	0	COM-NO ₂					
0	0	1	1	COM-NO ₃					
0	1	0	0	COM-NO ₄					
0	1	0	1	COM-NO ₅					
0	1	1	0	COM-NO ₆					
0	1	1	1	COM-NO7					
	NO and COM pins are identical and interchangeable. Either may be considered an input or output; signals pass equally well in either direction.								



Figure 2. Logic Diagram

MAXIMUM RATINGS

Symbol		Parameter	Value	Unit
V _{EE}	Negative DC Supply Voltage	(Referenced to GND)	-7.0 to +0.5	V
V _{CC}	Positive DC Supply Voltage (Note 1)	(Referenced to GND) (Referenced to V _{EE})	-0.5 to +7.0 -0.5 to +7.0	V
V _{IS}	Analog Input Voltage		$V_{\mbox{\scriptsize EE}}$ –0.5 to $V_{\mbox{\scriptsize CC}}$ +0.5	V
V _{IN}	Digital Input Voltage	(Referenced to GND)	-0.5 to 7.0	V
I	DC Current, Into or Out of Any Pin		± 50	mA
T _{STG}	Storage Temperature Range		-65 to +150	°C
ΤL	Lead Temperature, 1 mm from Case	for 10 Seconds	260	°C
TJ	Junction Temperature under Bias		+ 150	°C
θ_{JA}	Thermal Resistance		164	°C/W
PD	Power Dissipation in Still Air		450	mW
MSL	Moisture Sensitivity		Level 1	
F _R	Flammability Rating	Oxygen Index: 30% – 35%	UL 94 V–0 @ 0.125 in	
V _{ESD}	ESD Withstand Voltage	Human Body Model (Note 2) Machine Model (Note 3) Charged Device Model (Note 4)	> 2000 > 200 > 1000	V
I _{LATCHUP}	Latchup Performance	Above V_{CC} and Below GND at 125°C (Note 5)	± 300	mA

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality Stresses exceeding those listed in the Maximum Ratings table may damage to should not be assumed, damage may occur and reliability may be affected. 1. The absolute value of $V_{CC} \pm |V_{EE}| \le 7.0$. 2. Tested to EIA/JESD22–A114–A. 3. Tested to EIA/JESD22–A115–A. 4. Tested to JESD22–C101–A.

5. Tested to EIA/JESD78.

RECOMMENDED OPERATING CONDITIONS

Symbol	Parameter		Min	Max	Unit
V_{EE}	Negative DC Supply Voltage	(Referenced to GND)	-5.5	GND	V
V _{CC}	Positive DC Supply Voltage	(Referenced to GND) (Referenced to V _{EE})	2.5 2.5	5.5 6.6	V
V _{IS}	Analog Input Voltage		V_{EE}	V _{CC}	V
V _{IN}	Digital Input Voltage	(Note 6) (Referenced to GND)	0	5.5	V
T _A	Operating Temperature Range, All Package Types		-55	125	°C
t _r , t _f	Input Rise/Fall Time (Channel Select or Enable Inputs)	$\begin{array}{l} {\sf V}_{CC} = 3.0 \; {\sf V} \; \pm \; 0.3 \; {\sf V} \\ {\sf V}_{CC} = 5.0 \; {\sf V} \; \pm \; 0.5 \; {\sf V} \end{array}$	0 0	100 20	ns/V

Functional operation above the stresses listed in the Recommended Operating Ranges is not implied. Extended exposure to stresses beyond the Recommended Operating Ranges limits may affect device reliability.

6. Unused digital inputs may not be left open. All digital inputs must be tied to a high-logic voltage level or a low-logic input voltage level.

DC CHARACTERISTICS - Digital Section (Voltages Referenced to GND)

			V.	Guaranteed Limit			
Symbol	Parameter	Condition	V _{CC} V	–55 to 25°C	≤85°C	≤125°C	Unit
V _{IH}	Minimum High-Level Input Voltage, Address or Inhibit Inputs		3.0 4.5 5.5	1.6 2.0 2.0	1.6 2.0 2.0	1.6 2.0 2.0	V
V _{IL}	Maximum Low–Level Input Voltage, Address or Inhibit Inputs		3.0 4.5 5.5	0.5 0.8 0.8	0.5 0.8 0.8	0.5 0.8 0.8	V
I _{IN}	Maximum Input Leakage Current, Address or Inhibit Inputs	V _{IN} = 6.0 or GND	0 V to 6.0 V	±0.1	±1.0	±1.0	μΑ
I _{CC}	Maximum Quiescent Supply Current (per Package)	Address or Inhibit and $V_{IS} = V_{CC}$ or GND	6.0	4.0	40	80	μΑ

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

DC ELECTRICAL CHARACTERISTICS – Analog Section

			v _{cc}	V _{EE}	Guara			
Symbol	Parameter	Test Conditions	V V	VEE	–55 to 25°C	≤85°C	≤125°C	Unit
R _{ON}	Maximum "ON" Resistance		3.0 4.5 3.0	0 0 -3.0	86 37 26	108 46 33	120 55 37	Ω
ΔR _{ON}	Maximum Difference in "ON" Resistance Between Any Two Channels in the Same Pack- age		3.0 4.5 3.0	0 0 -3.0	15 13 10	20 18 15	20 18 15	Ω
Rflat _(ON)	ON Resistance Flatness	V _{COM} = 1, 2, 3.5 V V _{COM} = 2, 0, 2 V	4.5 3.0	3.0	4 2	4 2	5 3	Ω
I _{NC(OFF)} I _{NO(OFF)}	Maximum Off–Channel Leakage Current	Switch Off $V_{IN} = V_{IL}$ or V_{IH} $V_{IO} = V_{CC} - 1.0$ V or V_{EE} +1.0 V (Figure 17)	6.0 3.0	0 -3.0	0.1 0.1	5.0 5.0	100 100	nA
I _{COM(ON)}	Maximum On–Channel Leakage Current, Channel–to–Channel	Switch On V _{IO} = V _{CC} –1.0 V or V _{EE} +1.0 V (Figure 17)	6.0 3.0	0 -3.0	0.1 0.1	5.0 5.0	100 100	nA

AC CHARACTERISTICS (Input $t_r = t_f = 3 \text{ ns}$)

					Guara −55 to 25°C		inteed Lin		
			Vcc	VEE					
Symbol	Parameter	Test Conditions	V	V	Min	Тур*	≤85°C	≤125°C	Unit
t _{BBM}	Minimum Break-Before-Make Time	$V_{IN} = V_{IL} \text{ or } V_{IH}$ $V_{IS} = V_{CC}$	3.0 4.5	0.0 0.0	1.0 1.0	6.5 5.0			ns
		$\begin{array}{ll} R_{L} = \ 300 \ \Omega, \ C_{L} = \ 35 \ pF \\ (Figure 19) \end{array}$	3.0	-3.0	1.0	3.5	-	-	

*Typical Characteristics are at 25°C.

AC CHARACTERISTICS (CL = 35 pF, Input $t_r = t_f = 3 \text{ ns}$)

				Guaranteed Limit							
		v _{cc}	V _{EE}	-	-55 to 25	o°C	≤8	35°C	≤1	25°C	
Symbol	Parameter	V V	VEE	Min	Тур	Max	Min	Max	Min	Max	Unit
t _{TRANS}	Transition Time (Address Selection Time) (Figure 18)	2.5 3.0 4.5 3.0	0 0 -3.0			40 28 23 23		45 30 25 25		50 35 30 28	ns
t _{ON}	Turn–on Time (Figures 14, 15, 20, and 21) Enable to N _O or N _C	2.5 3.0 4.5 3.0	0 0 -3.0			40 28 23 23		45 30 25 25		50 35 30 28	ns
tOFF	Turn–off Time (Figures 14, 15, 20, and 21) Enable to N _O or N _C	2.5 3.0 4.5 3.0	0 0 -3.0			40 28 23 23		45 30 25 25		50 35 30 28	ns

		Typical @ 25°C, $V_{CC} = 5.0 V$	
C _{IN}	Maximum Input Capacitance,Select Inputs	8	pF
C_{NO} or C_{NC}	Analog I/O	10	
C _{COM}	Common I/O	10	
C _(ON)	Feedthrough	1.0	

ADDITIONAL APPLICATION CHARACTERISTICS (GND = 0 V)

			v _{cc}	V	Тур	
Symbol	Parameter	Condition	V V	V _{EE} V	25°C	Unit
BW	Maximum On–Channel Bandwidth or Minimum Frequency Response	$V_{IS} = \frac{1}{2} (V_{CC} - V_{EE})$ Source Amplitude = 0 dBm (Figures 10 and 22)	3.0 4.5 6.0 3.0	0.0 0.0 0.0 -3.0	80 90 95 95	MHz
V _{ISO}	Off–Channel Feedthrough Isolation	f = 100 kHz; $V_{IS} = \frac{1}{2} (V_{CC} - V_{EE})$ Source = 0 dBm (Figures 12 and 22)	3.0 4.5 6.0 3.0	0.0 0.0 0.0 -3.0	-93 -93 -93 -93	dB
V _{ONL}	Maximum Feedthrough On Loss	$V_{IS} = \frac{1}{2} (V_{CC} - V_{EE})$ Source = 0 dBm (Figures 10 and 22)	3.0 4.5 6.0 3.0	0.0 0.0 0.0 -3.0	-2 -2 -2 -2	dB
Q	Charge Injection	V_{IN} = V_{CC} to $V_{EE,}$ f_{IS} = 1 kHz, t_r = t_f = 3 ns R_{IS} = 0 $\Omega,$ C_L = 1000 pF, Q = C_L * ΔV_{OUT} (Figures 16 and 23)	5.0 3.0	0.0 -3.0	9.0 12	рС
THD	Total Harmonic Distortion THD + Noise		6.0 3.0	0.0 -3.0	0.10 0.05	%

TYPICAL CHARACTERISTICS

100

100





Figure 8. Typical On Resistance $V_{CC} = 5.5 \text{ V}, V_{EE} = 0 \text{ V}$

6.0

3.0

5.5

TYPICAL CHARACTERISTICS



TYPICAL CHARACTERISTICS









Figure 16. Charge Injection versus COM Voltage



Figure 17. Switch Leakage versus Temperature



Figure 18. Channel Selection Propagation Delay







Figure 20. t_{ON}/t_{OFF}



Figure 21. t_{ON}/t_{OFF}



Channel switch Address and Inhibit/s test socket is normalized. Off isolation is measured across an off channel. On loss is the bandwidth of an On switch. V_{ISO} , Bandwidth and V_{ONL} are independent of the input signal direction.

 V_{ISO} = Off Channel Isolation = 20 Log $\left(\frac{VOUT}{VIN}\right)$ for V_{IN} at 100 kHz

 V_{ONL} = On Channel Loss = 20 Log $\left(\frac{V_{OUT}}{V_{IN}}\right)$ for V_{IN} at 100 kHz to 50 MHz

Bandwidth (BW) = the frequency 3 dB below VONL

Figure 22. Off Channel Isolation/On Channel Loss (BW)/Crosstalk (On Channel to Off Channel)/V_{ONL}



Figure 23. Charge Injection: (Q)

TYPICAL OPERATION





Figure 24. 5.0 Volts Single Supply $V_{CC} = 5.0 \text{ V}, \text{ V}_{EE} = 0$

Figure 25. Dual Supply $V_{CC} = 3.0 \text{ V}, V_{EE} = -3.0 \text{ V}$

ORDERING INFORMATION

Device	Package	Shipping [†]
NLAST4051DTR2G	TSSOP-16 (Pb-Free)	2500 / Tape & Reel
NLVAST4051DTR2G*	TSSOP-16 (Pb-Free)	2500 / Tape & Reel

+For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

*NLV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC–Q100 Qualified and PPAP Capable.





DOCUMENT NUMBER:	98ASH70247A	Electronic versions are uncontrolled except when accessed directly from the Document Repositor Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.					
DESCRIPTION:	TSSOP-16	-	PAGE 1 OF 1				
		stries, LLC dba ON Semiconductor or its subsidiaries in the United States					

ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. ON Semiconductor does not convey any license under its patent rights nor the rights of others.

onsemi, ONSEMI, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and calcular performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

TECHNICAL SUPPORT

onsemi Website: www.onsemi.com

Email Requests to: orderlit@onsemi.com

North American Technical Support: Voice Mail: 1 800-282-9855 Toll Free USA/Canada Phone: 011 421 33 790 2910

Europe, Middle East and Africa Technical Support: Phone: 00421 33 790 2910 For additional information, please contact your local Sales Representative